

Model Number:	Approvals:
Accessories:	
Job:	Type:

**TECHNICAL SPECIFICATIONS**

Input Voltage: 120/277V, 60Hz  
 Input Wattage: 3.5 watts  
 Emergency Operation: 90 minutes  
 Minimum Initial Illumination: (1) lamp 600-700 lumens  
 Weight: 2.5 lbs  
 Operating Temperature Range: 0°C – 50°C

**LAMPS OPERATED<sup>1</sup>**

	Lamp	Wattage
<b>LINEAR</b>	T5	8-21W
	T8	17-110W
	T10	17-110W
	T12	17-110W
	Circline	-
	U-Shape	20-40W
	<b>CFL</b>	4-Pin
Long Compact		18-36W
2-Pin		-



The XEB-7-B-LM Fluorescent Emergency Ballast allows the same fixture to be used for both normal and emergency operation when used in conjunction with an AC ballast. If used in an emergency only fixture, no AC ballast is necessary. In the event of a power failure, the XEB-7-B-LM instantly switches to the emergency mode and operates one of the existing lamps for 90 minutes. The unit contains a battery, charger, and electronic circuit in a single can. The XEB-7-B-LM can be mounted in the wireway or on top of the fixture, and is U.L. Listed for factory installation or retrofit applications. The XEB-7-B-LM has a minimal initial output of 600-700 lumens for one lamp.

**FEATURES**

- U.L. Listed for factory or field installation
- Will cold start and operate all specified lamps
- Compatible with ECO/low mercury lamps
- Listed 90 minute emergency run time, 24 hour recharge time
- High temperature, maintenance-free, NiCad battery with 7-10 year life expectancy
- Includes test switch and charge indicator accessory kit
- Meets or exceeds all National Electrical Code and Life Safety Code Emergency Lighting Requirements
- Painted, steel case
- 120/277V dual primary, 60Hz input



SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

**CASE DIMENSIONS**

Length 9.4"  
 Width 2.4"  
 Height 1.5"  
 Mounting Center 8.9"

**WARRANTY**

The Exitronix XEB-7-B-LM is warranted for five (5) years from date of purchase. Warranty covers only Exitronix emergency ballasts installed as directed, and used under normal conditions. Warranty does not cover physical damage, abuse, or acts of God.

**CONFORMANCE TO CODES & STANDARDS**

U.L. 924 listed for factory installations or field retrofit applications. Emergency illumination time exceeds the National Electric Code (NEC), Life Safety Code (NFPA-LSP), and U.L. 924 90 minute requirements.

**REMOTE MOUNTING**

When battery packs are remote mounted, the remote distance cannot exceed 1/2 of the distance from ballast to lamp, as specified by the AC ballast manufacturer. The maximum allowable remote mounting distance is 50 ft. from the lamp.

<sup>1</sup> These ballasts may operate other lamp types, please consult factory for compatibility.