

Model Number:	Approvals:
Accessories:	
Job:	Type:

TECHNICAL SPECIFICATIONS

Input Voltage: 120/277V, 60Hz
 Input Wattage: 2.5 watts
 Emergency Operation: 90 minutes
 Minimum Initial Illumination: (1) lamp 350-400 lumens
 Weight: 1.5 lbs
 Operating Temperature Range: 0°C – 55°C

LAMPS OPERATED¹

	Lamp	Wattage
LINEAR	T5	8-28W
	T8	17-40W
	T10	17-40W
	T12	17-40W
	Circline	20-40W
	U-Shape	32-40
	CFL	4-Pin
Long Compact		18W
2-Pin		-



The XEB-5-B-LM-LP Low Profile Fluorescent Emergency Ballast allows the same fixture to be used for both normal and emergency operation when used in conjunction with an AC ballast. If used in an emergency only fixture, no AC ballast is necessary. In the event of a power failure, the XEB-5-B-LM-LP instantly switches to the emergency mode and operates one of the existing lamps for 90 minutes. The unit contains a battery, charger, and electronic circuit in a single can. The XEB-5-B-LM-LP can be mounted in the wireway or on top of the fixture, and is UL Listed for factory installation or retrofit applications.

FEATURES

- UL Listed for factory or field installation
- Will cold start and operate all specified lamps
- Compatible with ECO/low mercury lamps
- Listed 90 minute emergency run time, 24 hour recharge time
- High temperature, maintenance-free, NiCad battery with 7-10 year life expectancy
- Includes test switch and charge indicator accessory kit
- Meets or exceeds all National Electrical Code and Life Safety Code Emergency Lighting Requirements
- Painted, steel case
- 120/277V dual primary, 60Hz input
- Alternative international voltages models available
- Damp location rated

CASE DIMENSIONS

Length 9.6"
 Width 2.12"
 Height 1.12"
 Mounting Center 8.9"

WARRANTY

The Exitronix XEB-5-B-LM-LP is warranted for five (5) years from date of purchase. Warranty covers only Exitronix emergency ballasts installed as directed, and used under normal conditions. Warranty does not cover physical damage, abuse, or acts of God.



SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

CONFORMANCE TO CODES & STANDARDS

UL 924 listed for factory installations or field retrofit applications. Emergency illumination time exceeds the National Electric Code (NEC), Life Safety Code (NFPA-LSP), and UL 924 90 minute requirements.

REMOTE MOUNTING

When battery packs are remote mounted, the remote distance cannot exceed 1/2 of the distance from ballast to lamp, as specified by the AC ballast manufacturer. The maximum allowable remote mounting distance is 50 ft. from the lamp.

¹ These ballasts may operate other lamp types, please consult factory for compatibility.