



SORAA LED MR16 Magnetic Transformer & Dimmer Compatibility

Combined Transformers & Dimmers, North America

| TRANSFORMERS | | DIMMERS | | | | | | |
|-----------------------|---------------------------------------------------|------------------------|-------------------------|------------------|------------------------|-------------------------------|-------------------------------|-----------------------------------------------------------------------|
| | | Lutron Grafik Eye 3000 | Lutron Skylark SLV-600P | Lutron DVLV-600P | Lutron Ceana CNLV-600P | Lutron Radio RAZ RRD-6NA 600W | Lutron Radio RAZ RRD-10D 800W | MARLIN CONTROLS Stellar DIMMING CABINET P/N 6-3-08-20-3-103T with RMS |
| Cooper | TF-149911 | 11% | F | F | F | NT | NT | 7% |
| Cooper | TF 149911-TP 120 | 10% | F | F | F | NT | NT | 9% |
| Linea | 701970 | 13% | F | F | F | NT | NT | 9% |
| Hasler Electric | MI-5481E | 10% | F | F | F | NT | NT | 9% |
| Juno | 310-1333 | 13% | F | F | F | NT | NT | 10% |
| Orientronic | DLR1250BN | 13% | 27% | 27% | 27% | NT | NT | 8% |
| Q-TRAN | QT-50-75CK-PT-RC Date 11/11 | 10% | 23% | 23% | 23% | NT | NT | 1 lamp: F 2,3 lamps: 10% |
| Q-TRAN | QT50SV-120/12-RC | 13% | 30% | 30% | 30% | NT | NT | NT |
| Q-TRAN | QT20-120/12-TP-RC | 9% | 28% | 28% | 28% | NT | NT | 9% |
| Q-TRAN | QT10-120/12-TP-RC | 9% | 24% | 24% | 24% | NT | NT | 8% |
| Hammond Manufacturing | 166Q12 | 13% | F | F | F | NT | NT | 10% |
| Q-TRAN | Q6S-DC-120-12 (Rectified) | 13% | 21% | 21% | 21% | NT | NT | 10% |
| Q-TRAN | QTM60-DC+CAP (Rectified + Filtered_ | 10% | F | F | F | NT | NT | 1 lamp: F 2,3 lamps: 24% |
| MDL Corp | 315-0071A – IRIS RPN3MR Fixture Normal Tap | NT | 27% | 33% | NT | 9% | 10% | NT |
| MDL Corp | 315-0071A – IRIS RPN3MR Fixture dimmerl Tap | NT | 28% | 35% | NT | NT | NT | NT |
| MDL Corp | 315-0126 – 12.3V | NT | 26% | 32% | NT | 9% | 8% | NT |

Updated 12/19/13

Key **XX%** = Low dimming Range **F**= Fail **NT**= Not Tested