



CustomerService | Ballasts / Transformers | Lamps | Custom Products | Company



## FLUORESCENT IN-FIXTURE ELECTRONIC BALLAST

10 BALLASTS OPERATE 132 LAMPS IN 860 COMBINATIONS

- Solid State Electronics • High Power Factor • Small Case Size
- Lightweight • Versatile • Energy Saving

WH3-120-C

### Ballast Specifications

Maximum Power: 64W

Model Number: WH3-120-C

Maximum Current: .56 AMP

Operating Voltage: 120 VAC

Product Photo: [click here to view](#)

### Case Specifications

Black/White Wires: 12"

Red/Yellow Wires: 12"

Ballast Case Size: H 1" x W 2.5" x L 3.8"

Ballast Weight: 10 oz.

Case Quantity: 50 pcs.

Case Weight: 32 lbs.

### Specifications Common to all WorkHorse Ballasts

Frequency: 50/60 Hz

ATHD: Meets ANSI C82.11-1993

Protection/Overcurrent: Fuse

Protection/Voltage Transients: MOV (PER ANSI C82.11 - 1993)

EMI/RFI: FCC PART 18-A

Regulatory Approvals: UL & cUL Listed Type 1 Outdoors

High Power Factor: >.90

Open Circuit Voltage: 600 V RMS Max.

Min. Operating Temp.: -20\* F (-30\* C)

Max. Case Temp.: 158\* F (70\* C)

Lamp Starting Mode: Instant Start

Class P: Thermal

Sound Rating: A