



CustomerService | Ballasts / Transformers | Lamps | Custom Products | Company



FLUORESCENT IN-FIXTURE ELECTRONIC BALLAST

10 BALLASTS OPERATE 132 LAMPS IN 860 COMBINATIONS

- Solid State Electronics • High Power Factor • Small Case Size
- Lightweight • Versatile • Energy Saving

WH8-120-L

Ballast Specifications

Maximum Power: 220W

Model Number: WH8-120-L

Maximum Current: 1.8 AMP

Operating Voltage: 120 VAC

Product Photo: [click here to view](#)

Case Specifications

Black/White Wires: 18"

Red/Yellow Wires: 36"

Ballast Case Size: H 1" x W 1.72" x L 18.25"

Ballast Weight: 34 oz.

Case Quantity: 25 pcs.

Case Weight: 57 lbs.

Specifications Common to all WorkHorse Ballasts

Frequency: 50/60 Hz

ATHD: Meets ANSI C82.11-1993

Protection/Overcurrent: Fuse

Protection/Voltage Transients: MOV (PER ANSI C82.11 - 1993)

EMI/RFI: FCC PART 18-A

Regulatory Approvals: UL & cUL Listed Type 1 Outdoors

High Power Factor: >.90

Open Circuit Voltage: 600 V RMS Max.

Min. Operating Temp.: -20* F (-30* C)

Max. Case Temp.: 158* F (70* C)

Lamp Starting Mode: Instant Start

Class P: Thermal

Sound Rating: A