



Dimmer Compatibility Chart on Dimmable LED lamps from Overdrive

No.	Make of Dimmer	Overdrive Item No. >	501	502	503	504	505	506	514	517	524
		Overdrive Model No. >	L5A19/DIM/30K (A-TYPE 5W)	L8A19/DIM/30K (A-TYPE 8W)	L8PAR20DIM/NFL/30K (PAR20 8W)	L13PAR30DIM/FL/30K (PAR30 13W)	L20PAR38DIM/FL/30K (PAR38 23W)	L8A19/DIM/50K (A-TYPE 8W)	L11R30DIM/30K (11W R30)	L4CDDIM/E12/30K (3.5W CANDLE)	L11R30DIM/50K (11W R30)
		Dimmer Model no.									
1-1	LEVITON	C20-6683-IW	✓	✓	✓	✓	✓	✓	✓	✓	✓
1-2		C20-6681-IW	✓	✓	✓	✓	✓	✓	✓	✓	✓
1-3		RPI06-1LI	✓	✓	✓	✓	✓	✓	✓	✓	✓
1-4		6674-10W	✓	✓	✓	✓	✓	✓	✓	✓	✓
1-5		6615-POW	✗	✗	✗	✓	✓	✗	✓	✗	✓
1-6		R15-PI06-1SE	✓	✓	✓	✓	✓	✓	✓	✓	✓
1-7		O10-IP04-1LZ	✗	✓	✓	✓	✓	✓	✓	✗	✓
2-1	LUTRON	TTCL-100H-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-2		D-600PH-DK	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-3		DVLV-600P-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-4		NTLV-600-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-5		DVELV-300P-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-6		DV-603PG-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-7		NLV-600-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-8		CTCL-153PDH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-9		D-603PH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-10		TT-300NLN-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-11		MRF2-3PD-1-1WH(Digital)	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-12		MA-600-WH(Digital)	✗	✗	✗	✗	✗	✗	✗	✗	✗
2-13		MAW-600(Digital)	✗	✗	✗	✗	✗	✗	✗	✗	✗
2-14		MRF2-6ND-120-WH(Digital)	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-15		RRD-10ND-WH(Digital)	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-16		VTELV-600M-B-WH(Digital)	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-17		MAELV-600-WH(Digital)	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-18		MRF2-6ELV-120-WH(Digital)	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-19		TG-603PGH-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-20		AYLV-600P-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-21		TG-603PGH-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
2-22		S-600PR-WH	✓	✓	✓	✓	✓	✓	✓	✓	✓
3-1	LEGRAND	DRD4-B(Digital)	✓	✓	✓	✓	✓	✓	✓	✓	✓
4-1	PASS&SEYMORE	CD703-PW	✓	✓	✓	✓	✓	✓	✓	✓	✓
4-2		CDLV703-P	✓	✓	✓	✓	✓	✓	✓	✓	✓
4-3		D703-PTC	✓	✓	✓	✓	✓	✓	✓	✓	✓
4-4		DLV703-P	✓	✓	✓	✓	✓	✓	✓	✓	✓

Note: This document is property of "OVERDRIVE Electronics Pvt. Ltd" and should not be copied without written permission. This data sheet is not controlled copy & is subject to change without notice.