

Can Compatibility* – LR6/LR6C

Capri

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
CIND6		✓		Remove "L" bracket. Unclip Edison socket from bracket.
CR1		✓		Remove "L" bracket. Unclip Edison socket from bracket.
CR1NB	✓			
CR1NBQP	✓			
CR1QP		✓		Remove "L" bracket. Unclip Edison socket from bracket.
CRR1		✓		Remove "L" bracket. Unclip Edison socket from bracket.
CRR1NB	✓			
CRR1NBQP	✓			
CRR1QP		✓		Remove "L" bracket. Unclip Edison socket from bracket.
PR1		✓		Remove "L" bracket. Unclip Edison socket from bracket.
PR75ASIC		✓		Remove "L" bracket. Unclip Edison socket from bracket.
PR75IC		✓		Remove "L" bracket. Unclip Edison socket from bracket.
QL1		✓		Remove "L" bracket. Unclip Edison socket from bracket.
QL1NB	✓			
QL1NBQP	✓			
QL1QP		✓		Remove "L" bracket. Unclip Edison socket from bracket.
R150ASIC		✓		Remove "L" bracket. Unclip Edison socket from bracket.

*Compatibility was determined based on whether the LR6 would fit within the identified can when appropriately modified. The presence of a can on the compatibility chart is not a guaranty or warranty of the compatibility of the LR6 in any particular installation. The absence of a can from the compatibility chart does not indicate that the LR6 is not compatible with a particular can. In any install, the installer should make sure that the LR6 is securely retained in the fixture at the time of install.

Can Compatibility* – LR6/LR6C

Halo

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
H7ICAT		✓		Remove "L" bracket and backing plate. Unclip socket from backing plate.
H7ICATNB	✓			
H7ICT		✓		Remove "L" bracket and backing plate. Unclip socket from backing plate.
H7ICTNB	✓			
H7RICAT		✓		Remove "L" bracket and backing plate. Unclip socket from backing plate.
H7RICT		✓		Remove "L" bracket and backing plate. Unclip socket from backing plate.
H7RT		✓		Remove "L" bracket. Unclip Edison socket from bracket.
H7T	✓			
H7TNB			✓	
H7UICAT			✓	
H7UICT			✓	

*Compatibility was determined based on whether the LR6 would fit within the identified can when appropriately modified. The presence of a can on the compatibility chart is not a guaranty or warranty of the compatibility of the LR6 in any particular installation. The absence of a can from the compatibility chart does not indicate that the LR6 is not compatible with a particular can. In any install, the installer should make sure that the LR6 is securely retained in the fixture at the time of install.

Can Compatibility* – LR6/LR6C

Juno

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
IC2		✓		Loosen two socket bracket screws and turn socket bracket to free it. Bend side tabs down slightly.
IC22		✓		Must remove socket bracket by removing the two mounting screws.
IC22R		✓		Loosen socket bracket screw and turn socket bracket to free it. Bend side tabs down slightly. Loosen backing plate slide nuts. Pry backing plate slide over slide stops. Bottom out backing plate.
IC22W		✓		Loosen socket bracket screw and turn socket bracket to free it. Bend side tabs down slightly. Loosen backing plate slide nuts. Pry backing plate slide over slide stops. Bottom out backing plate.
IC23		✓		Loosen socket bracket screw and turn socket bracket to free it. Bend side tabs down slightly.
IC2W		✓		Loosen two socket bracket screws and turn socket bracket to free it. Bend side tabs down slightly.
TC2		✓		Loosen two socket bracket screws and turn socket bracket to free it. Bend side tabs down slightly.
TC2R		✓		Loosen socket bracket screw and turn socket bracket to free it. Bend side tabs down slightly. Can depth must be set > 6" .
TC2W		✓		Loosen two socket bracket screws and turn socket bracket to free it. Bend side tabs down slightly.

*Compatibility was determined based on whether the LR6 would fit within the identified can when appropriately modified. The presence of a can on the compatibility chart is not a guaranty or warranty of the compatibility of the LR6 in any particular installation. The absence of a can from the compatibility chart does not indicate that the LR6 is not compatible with a particular can. In any install, the installer should make sure that the LR6 is securely retained in the fixture at the time of install.

Can Compatibility* – LR6/LR6C

Lightolier

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
1102P1			✓	
1104IC		✓		Remove socket assembly from can. Bend short clips back. Leave the long clips as is. Screw LLF fixture into Edison socket and fully extend LLF retaining clips. Push assembly into can and turn 1/4 turn. To remove fixture, unscrew from Edison socket.
1104ICN		✓		Remove socket assembly from can. Bend short clips back. Leave the long clips as is. Screw LLF fixture into Edison socket and fully extend LLF retaining clips. Push assembly into can and turn 1/4 turn. To remove fixture, unscrew from Edison socket.
1104ICR		✓		Remove socket assembly from can. Bend short clips back. Leave the long clips as is. Screw LLF fixture into Edison socket and fully extend LLF retaining clips. Push assembly into can and turn 1/4 turn. To remove fixture, unscrew from Edison socket.
1104ICX			✓	
1104ICXN			✓	

Lithonia

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
L7X	✓			
L7XR	✓			
LC6	✓			
LP6			✓	

*Compatibility was determined based on whether the LR6 would fit within the identified can when appropriately modified. The presence of a can on the compatibility chart is not a guaranty or warranty of the compatibility of the LR6 in any particular installation. The absence of a can from the compatibility chart does not indicate that the LR6 is not compatible with a particular can. In any install, the installer should make sure that the LR6 is securely retained in the fixture at the time of install.

Can Compatibility* – LR6/LR6C

Liton Lighting

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
LH7IC-LLF		✓		Remove "L" bracket and backing plate. Unclip socket from backing plate.
LH7-LLF	✓			
LH7R-LLF		✓		Remove "L" bracket. Unclip Edison socket from bracket.

Progress

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
P187-TG			✓	
P821-AT		✓		Must remove Edison socket from spring clips. Spring clips must then be bent back into the can. Cutting spring clips is another option. Reflector can be left in place.
P87-AT			✓	
P87-ATQC		✓		Must remove Edison socket from spring clips. Spring clips must then be bent back into the can. Cutting spring clips is another option.

*Compatibility was determined based on whether the LR6 would fit within the identified can when appropriately modified. The presence of a can on the compatibility chart is not a guaranty or warranty of the compatibility of the LR6 in any particular installation. The absence of a can from the compatibility chart does not indicate that the LR6 is not compatible with a particular can. In any install, the installer should make sure that the LR6 is securely retained in the fixture at the time of install.

Can Compatibility* – LR6/LR6C

Seagull

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
1107		✓		Remove socket bracket wingnut and screw. Remove socket bracket. Unclip socket from bracket.
1108		✓		Remove socket bracket wingnut and screw. Remove socket bracket. Unclip socket from bracket.
1118		✓		Remove socket bracket wingnut and screw. Remove socket bracket. Unclip socket from bracket.
1119			✓	
1128		✓		Remove socket bracket wingnut and screw. Remove socket bracket. Unclip socket from bracket.
1128QC		✓		Remove socket bracket wingnut and screw. Remove socket bracket. Unclip socket from bracket.

Quorum International

Part Number	Compatible as is	Compatible with modifications	Not compatible	Recommended modifications
903		✓		Remove "L" bracket. Unclip Edison socket from bracket.

*Compatibility was determined based on whether the LR6 would fit within the identified can when appropriately modified. The presence of a can on the compatibility chart is not a guaranty or warranty of the compatibility of the LR6 in any particular installation. The absence of a can from the compatibility chart does not indicate that the LR6 is not compatible with a particular can. In any install, the installer should make sure that the LR6 is securely retained in the fixture at the time of install.