

MR16 Transformer Compatibility Chart

Brand	Model	Input Voltage (VAC/Hz)	Power Rating (W)	Type	Number of MR16s per Transformer					
					1	2	3	4	5	6
Advance	71A9743	120 VAC, 60 Hz	75	MT	G	G	G	G	G	G
Beal Pritchett (BP)	DINGO60	240V, 50Hz	60	ET	F	F	G	G	G	G
CHD	HUA1200600X2L	120 VAC, 60 Hz	60	ET	F	F	G	G	G	F
Crompton	CLED3	230-240 VAC, 50-60 Hz	12	ET	G	N/A	N/A	N/A	N/A	N/A
ELG	250LED100W	120 VAC, 60 Hz	100	ET	G	G	G	G	G	G
	250LED10W	120 VAC, 60 Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
	250AT075T	120 VAC, 60 Hz	75	MT	G	G	G	G	G	G
EYE LEDS	5011922UC	120 VAC, 60 Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
EYE LEDS	AZ09	230-240 VAC, 50-60 Hz	12	ET	G	N/A	N/A	N/A	N/A	N/A
Hatch	RS12-15M-LED	120 VAC, 50-60 Hz	15	ET	G	G	N/A	N/A	N/A	N/A
	PS12-20L	120 VAC, 60 Hz	20	ET	F	F	G	N/A	N/A	N/A
	RS12-30M-LED	120 VAC, 50-60 Hz	30	ET	G	G	G	G	N/A	N/A
	RS12-60M	120 VAC, 50-60 Hz	60	ET	F	F	F	G	G	G
	VSI2-60W	120 VAC, 50-60 Hz	60	ET	F	F	F	F	G	G
	VSI2-60WD	120 VAC, 50-60 Hz	60	ET	F	G	G	G	G	F
	RS12-80M	120 VAC, 50-60 Hz	80	ET	F	F	F	G	G	G
Hermosa	RS12-60M-LED	120 VAC, 50-60 Hz	60	ET	G	G	G	G	G	G
	ET105B60	230V, 50Hz	60	ET	G	G	G	G	G	G
IST	IDM011152	230-240 VAC, 50-60 Hz	11	ET	G	N/A	N/A	N/A	N/A	N/A
LCI	i60e	230 VAC, 50-60 Hz	60	ET	F	F	G	G	G	G
Lightech	LET-60	120 VAC, 50-60 Hz	60	ET	F	F	F	F	F	F
	LET-75	120 VAC, 50-60 Hz	75	ET	F	F	F	F	F	F
Ligro	E12SC50SA	230 VAC	50	MT	F	G	G	F	G	F
Luxalite	GD32LH	220-240 VAC, 50-60 Hz	55	ET	G	G	G	G	G	G
Lumex	MTR50/12 EN-61558	220VAC, 50 Hz	50	MT	G	G	G	G	G	G
MDL	319-0103	120 VAC, 50-60 Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
Mirano	BLNET-L50C 50W	220 VAC, 50-60Hz	50	ET	G	G	G	G	G	G
Niko	320-00112	230 VAC, 50 Hz	105	ET	F	G	G	F	G	F
Nobile	EN-80D	230 VAC, 50-60 Hz	80	ET	G	G	G	G	G	G
	EN-80D2	230 VAC, 50-60 Hz	80	ET	G	G	G	G	F	F
	EN-110D	230 VAC, 50-60 Hz	110	ET	G	G	G	G	G	G
	EN-110D2	230 VAC, 50-60 Hz	110	ET	F	F	F	F	F	F
Osram	ET-REDBACK	230-240 VAC, 50-60 Hz	60	ET	G	G	G	G	G	G
	HTM 150/230-240	230-240 VAC, 50-60 Hz	150	ET	G	G	G	G	G	G
Philips	Primaline 105 230-240	230-240 VAC, 50-60 Hz	105	ET	G	G	G	G	G	G
	Xitanium 10W Dimmable	220-240 VAC, 50-60 Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
	ET-S60220-240	220-240 VAC, 50-60 Hz	60	ET	F	F	F	F	F	F
	9137-100-536	220-240 VAC, 50-60 Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
	9137-100-538	220-240 VAC, 50-60 Hz	30	ET	G	G	G	G	N/A	N/A
Sunrise	H0050-497	120 VAC, 50-60 Hz	50	MT	G	G	G	G	G	G
Teca	100D8512S	120VAC, 60 Hz	100	MT	G	G	G	G	G	G
Tridonic	TM50-2	240VAC, 50-60Hz	50	MT	G	G	G	G	G	G
	VIPER 22176074	230-240 VAC, 50-60 Hz	105	ET	F	G	G	F	F	F
	VIPER 22176072	230-240 VAC, 50-60 Hz	105	ET	F	F	F	F	F	G
	Possum	230-240 VAC, 50-60 Hz	3.45	ET	F	F	F	F	F	F
VadsBO	SET70RE-1	220-240 VAC, 50 Hz	70	ET	F	F	F	G	F	G
Vike	VB60PL	230-240 VAC, 50-60 Hz	60	ET	G	G	G	G	G	F
Vossloh Schwabe	EST 70/12.380	230-240 VAC, 50-60 Hz	70	ET	F	F	F	F	F	F
	EST 105/12.381	230-240 VAC, 50-60 Hz	105	ET	F	F	G	G	G	G
	EST 150/12.622	230-240 VAC, 50-60 Hz	150	ET	G	G	G	G	G	F
WAC	EN-12100-R-AR	120 VAC, 50-60 Hz	100	ET	G	G	G	G	G	G
Wang	WH-60IE2CA-2L	120 VAC, 60 Hz	60	ET	F	F	G	G	G	F

Et - Electronic Transformer MT - Magnetic Transformer G - Good F - Flickers N/A - Exceeds Transformer Recommended Power



Preliminary. Specifications are typical values and may change without notification.
Copyright © Lighting Science Group Corporation 2011 All rights reserved.