
NS-22 Albalite Lens with Metal Trim

TRIM DIMENSIONS



Trim OD: 5" Height: 1-5/8"

FEATURES

<u>Trim</u> High grade albalite lens attached to metal trim.

Mounting

Trim includes three trim clips that securely mount trim in housing.

Compatible Housings

Compatible with Line Voltage and Compact Fluorescent housings. See individual specification sheets for more information.

<u>Lamp</u>

Line Voltage 50W R20/PAR20 Max. (NS-401QAT; NSIC-401QAT; NSR-404QAT) Compact Fluorescent 13W Quad/Triple (NS-406Q; NS-406EL; NSR-408Q; NSR-408EL)

Labels and Listings

cULus Listed for Wet Location when used with compatible housing.

ENORALIGHTING.


Туре

Project


Catalog No.


Lamp/Wattage

HOUSING DIMENSIONS





NSIC-401QAT







Ceiling Cut-out






NS-406Q / NS-406EL





NSR-408Q / NSR-408EL





Compatible Housings

	LINE VOLTAGE			
Albalite Lens with Metal Trim	Item Number	Installation Type	Lamp	Dimensions
NS-22B: Albalite Lens with Black Metal Trim	□NS-401QAT	Non-IC Air-Tight New Const.	50W R/PAR20	W: 5-5/8" L: 8-1/2" H: 5-5/8"
NS-2222: Albalite Lens with Branze Metal Trim	NSIC-401QAT	IC Air-Tight New Construction	50W R/PAR20	W: 5-1/4" L: 8-1/2" H: 6-3/8"
	NSR-404QAT	Non-IC Air-Tight Remodel	50W R/PAR20	W: 4-1/4" L: 11-1/4" H: 5-5/8"
NS-22C: Albalite Lens with Chrome Metal Trim	COMPACT FLUORESCENT			
NS-22CO: Albalite Lens with Copper Metal Trim	□NS-406Q	Non-IC New Constr., Magnetic	13W Quad	W: 6-1/4" L: 10" H: 5-1/2"
NS-22G: Albalite Lens with Gold Metal Trim	NS-406EL	Non-IC New Constr., Electronic	13W Quad/Triple	W: 6-1/4" L: 9" H: 5-1/2"
NS-22N: Albalite Lens with Natural Metal Trim	NSR-408Q	Non-IC Remodel, Magnetic	13W Quad	W: 4-3/4" L: 11-7/8" H: 5-1/2"
NS-22W: Albalite Lens with White Metal Trim	NSR-408EL	Non-IC Remodel, Electronic	13W Quad/Triple	W: 4-3/4" L: 11-7/8" H: 5-1/2"



6505 Gayhart St., Commerce, CA 90040 www.noralighting.com • Specifications subject to change without notice. © 2011 Phone: 800.686.6672 • FAX: 800.500.9955 • e-mail: nora@noralighting.com