Product Details Page 1 of 1



Product 59042

Number:

Order 75PAR16/HAL/NFL30 130V

Abbreviation:

General Tungsten Halogen CAPSYLITE Designer 16 Medium Base 75Watt

Description: 130Volt Narrow Flood Beam

| Product Information | |
|-----------------------------------|----------------------------------|
| Abbrev. With Packaging Info. | 75PAR16HALNFL30 130V 15/CS 1/SKU |
| Approx. Lumens | 900 |
| Average Rated Life (hr) | 2000 |
| Base | E26 Medium |
| Beam Angle (deg) | 30 |
| Beam Type | NFL |
| Bulb | PAR16 |
| Centerbeam Candlepower (cp) | 1900 |
| Class | C (gas) |
| Color Rendering Index (CRI) | 100 |
| Color Temperature/CCT (K) | 2900 |
| Diameter (in) | 2.000 |
| Diameter (mm) | 50.80 |
| Ecologic | YES |
| Family Brand Name | CAPSYLITE DESIGNER 16® |
| Filament | CC-8 |
| Horizontal Beam Angle (deg) | 30 |
| Lamp Finish | Reflector |
| Maximum Overall Length - MOL (in) | 2.875 |
| Maximum Overall Length - MOL (mm) | 73.025 |
| Nominal Voltage (V) | 130.00 |
| Nominal Wattage (W) | 75.00 |
| Vertical Beam Angle (deg) | 30 |



Footnotes

- For Indoor Use only.
- In base up operation, heat may eventually deteriorate paper-lined or plastic sockets.
- Approximate life for 130 volt tungsten halogen lamps operated at 120 volts is within the value calculated using the recommended equations for standard incandescent lamps, as set forth in the IES Handbook, 8th edition. Because of the uncertain nature of the halogen cycle on the coil when operated at less than rated voltage, life of tungsten halogen lamps varies considerably and unpredictably. OSRAM SYLVANIA does not recommend operation at other than rated voltage.
- @ 120 volts, approximate 66 watts, 685 lumens, 4000 hours